



VHF AND UHF TRANSCEIVERS

IC-F3062T

(VHF transceiver with 10-keypad)

IC-F4062T

(UHF transceiver with 10-keypad)

IC-F3062S

(VHF transceiver without 10-keypad)

IC-F4062S

(UHF transceiver without 10-keypad)



F3062 F4062 Series



Icom Inc.

ADVANCED TECHNOLOGY FOR THE FU



▲ IC-F3062T

▲ IC-F4062S

VHF TRANSCEIVERS

IC-F3062T

With 10-keypad

IC-F3062S

Without 10-keypad

UHF TRANSCEIVERS

IC-F4062T

With 10-keypad

IC-F4062S

Without 10-keypad

IP54/55 Dust-protection and splash, water jet resistance

The IC-F3062 series meets IP54/55 requirements for dust-protection, splash and water jet resistance. Its durable construction is backed up by the aluminum die-cast chassis and polycarbonate casing, allowing reliable operation under harsh weather and environmental conditions.

Lithium-Ion battery pack

The supplied 2000mAh Li-Ion battery pack, BP-232, provides 14 hours* of operating time. Icom's rugged dual-rail guide securely locks the battery to the radio. The optional battery case BP-240 provides a convenient back up and great reassurance in an emergency.

* Typical operation Tx:Rx:Stand-by=5:5:90, power save on

Most popular signalings built-in

The IC-F3062 series has built-in 2-Tone, 5-Tone, CTCSS and DTCS signaling capabilities as standard for group communication or selective calling. Also, the IC-F3062 series can decode ten 2-Tone codes or eight 5-Tone codes on a channel. When a matched tone is received, the following actions are programmable for each code.

- Beep sound
- Auto TX
- Stun/kill radio
- Bell icon
- Answer back call
- Scan

Wide frequency range and large channel capacity

The IC-F3062 series covers a wide frequency range in one version (VHF 136–174 MHz, UHF 400–470MHz). The 512 memory channel capacity with 128 zones allows you to divide and store a variety of flexible channel groupings. Memory channel selection can be made with a simple rotation of the rotary channel knob. Wide, middle and narrow channel bandwidth (25/20/12.5kHz)* is also programmable.

* Programmable 25/12.5kHz or 20/12.5kHz

Voting mode scanning

The Voting mode scanning detects the S-meter level of repeater stations and automatically selects the strongest station, useful for roaming between 2 or more repeater sites. In addition, the IC-F3062 series has 10 scanning modes including priority scan and double priority scan.

UTURE NOW!

Full dot-matrix LCD

Using a large full dot-matrix LCD (32 × 18 mm), the IC-F3062 series shows upper and lower case characters clearly. The display setting is selectable from 1 line, 12 characters or 2 lines 24 characters via programming. The bottom row shows assigned functions to the [P0] to [P3] buttons.



Enhanced audio

The IC-F3062 series employs a BTL amplifier that increases the audio output and the built-in audio compander provides clear, low noise communications.

Built-in inversion-type voice scrambler

The built-in inversion type voice scrambler provides secure conversation as standard. When a more secure system is required, the 32 code non-rolling-type voice scrambler UT-109R and 1020 code rolling type UT-110R are available as an option.

BIIS 1200 compatible

The following selective calling and data features are available with the built-in BIIS system.

- 32 abbreviated call memories
- 7 group IDs
- 24-status Messages
- Send 12-character SDM (Short Data Message)
- Receive up to 95 characters of free text

Other features

- Built-in basic LTR® trunking capability.
- 8 DTMF autodial memories
- 2 step reduced power setting
- Power on password
- Busy, repeater lockout functions
- Radio stun and kill functions disable a lost or stolen unit over the air
- Surveillance function temporarily turns off the LED backlight and beep sound
- Powerful 5W output both VHF and UHF
- Flash CPU for future upgrade and more...


OPTIONS

Some options may not be available in some countries. Please ask your dealer for details.




Battery packs	Type and capacity	Operating time*	Output power
BP-230	Li-Ion 7.4V/ 800mAh	6 hours	5W
BP-231	Li-Ion 7.4V/1150mAh	8 hours	5W
BP-232	Li-Ion 7.4V/2000mAh	14 hours	5W
BP-240	AAA (LR03) batteries × 6	—	1W

* Operating time is approximate time (at 20°C). Tx: Rx: standby=5:5:90. Power save on.



BC-171 DESKTOP CHARGER + BC-147 AC ADAPTER
Charges the battery pack in 8–10 hours (approx.).



BC-160 DESKTOP CHARGER + BC-145 AC ADAPTER
Charges the BP-232 in 3 hours (approx.).
BC-119N + AD-106 + BC-145 is also available.



CP-17L CIGARETTE LIGHTER CABLE, OPC-515L DC POWER CABLE
For use with the BC-160 or BC-119N. (12–16V DC required).



BC-121N MULTI-CHARGER + AD-106 CHARGER ADAPTER + BC-157 AC ADAPTER
Rapidly charges up to 6 battery packs (Six AD-106s are required). Charging time: 3 hours (approx.) when BP-232 is attached.
OPC-656 DC POWER CABLE :For use with the BC-121N. (12–20V DC required).




MB-93 : Swivel type belt clip.
MB-94 : Alligator type. Same as supplied.
MB-96N : Swivel type belt hanger.
MB-96F : Fixed type belt hanger.



HS-94: Earhook headset with flexible boom microphone.
HS-95: Behind-the-head headset with flexible boom microphone.
HS-97: Throat microphone fits around your neck and picks up speech vibration.
VS-15C: PTT/VOX unit. Required when using these headsets with the transceiver.



HM-1315C : Compact type speaker microphone.
HM-1595C : Full size durable speaker microphone with revolving clip.



UT-109R: Up to 32 scrambling codes are available. 40-pin type.
UT-110R: Up to 1020 scrambling codes are available. 40-pin type.



SP-13: EARPHONE. AD-52: EARPHONE ADAPTER
Provides clear audio even in noisy environments.



ANTENNAS
FA-SC25V : 136–150MHz
FA-SC55V : 146–174MHz
FA-SC25U : 400–430MHz
FA-SC57U : 430–470MHz
FA-SC72U : 470–520MHz

Future digital mode capability

DIGITAL

An optional upgrade to 6.25kHz digital operation is planned in the near future.

Icom is currently researching the regulatory requirements for use in Europe for the 6.25kHz 4FSK/FDMA technology.



SPECIFICATIONS

GENERAL	
• Frequency range	: IC-F3062T/S 136–174MHz IC-F4062T/S 400–470MHz
• Number of channels	: 512 channels/128 zones
• Channel spacing	: 12.5kHz/20kHz/25kHz
• PLL channel step	: 2.5kHz, 3.125kHz
• Antenna impedance	: 50Ω
• Usable temperature range	: –25°C to +55°C
• Power supply requirement	: 7.2V DC nominal
• Current drain (at 7.2V DC; approx.):	
Transmit at 5W/5W	1.5A/1.8A (VHF/UHF)
Receive stand-by	95mA
rated output	600mA
• Dimensions	: 53 (W) × 136 (H) × 38.5 (D) mm (projections are not included)
• Weight (approx.)	: 340g (with BP-232)

TRANSMITTER	
• Output power	: 5W (VHF), 5W (UHF)
• Max. frequency deviation	: ±5.0/4.0/2.5kHz (Wide/middle/narrow)
• Frequency error	: ±1.0ppm
• Spurious emissions	: 0.25μW (≤1GHz) 1.0μW (>1GHz)
• Adjacent channel power	: 80dB typ. (Wide, middle) 70dB typ. (Narrow)
• Audio harmonic distortion	: 3% typ. (AF 1kHz, 40% deviation)
• Modulation limiting	: 60–100% of max. deviation
• Ext. microphone connector	: 9-pin multi connector/ 2.2kΩ

Measurements made in accordance with EN 300-086.
All stated specifications are subject to change without notice or obligation.

LTR is a registered trademark of E.F. Johnson Company.
All other trademarks are the properties of their respective holders.

RECEIVER	
• Intermediate frequency	: 1st 46.35MHz 2nd 450kHz
• Sensitivity	: –4dBμV typ. (emf, at 20dB SINAD)
• Squelch sensitivity	: –4dBμV typ. (emf, at threshold)
• Adjacent channel selectivity	: 75/75/68dB typ. (Wide/middle/narrow)
• Spurious response	: 70dB min.
• Intermodulation	: 67dB typ.
• Hum and noise ratio	: 55/53/50dB typ. (Wide/middle/narrow) (with CCITT filter)
• Audio output power	: 500mW typ. (at 5% distortion with an 8Ω load)
• External speaker connector	: 9-pin multi connector/ 8Ω

SUPPLIED ACCESSORIES (May differ according to version)



Icom Inc. 1-1-32, Kamiminami, Hirano-ku, Osaka 547-0003, Japan Phone: +81 (06) 6793 5302 Fax: +81 (06) 6793 0013

URL: <http://www.icom.co.jp/world/index.html>

Count on us!

Icom America Inc.

2380 116th Avenue NE,
Bellevue, WA 98004, U.S.A.
Phone: +1 (425) 454-8155
Fax: +1 (425) 454-1509
E-mail: sales@icomamerica.com
URL: <http://www.icomamerica.com>

Icom Canada

Glenwood Centre #150-6165 Highway 17,
Delta, B.C., V4K 5B8, Canada
Phone: +1 (604) 952-4266
Fax: +1 (604) 952-0090
E-mail: info@icomcanada.com
URL: <http://www.icomcanada.com>

Icom (Australia) Pty. Ltd.

A.B.N. 88 006 092 575
Unit 1 / 103 Garden Road,
Clayton VIC 3168 Australia
Phone: +61 (03) 9549 7500
Fax: +61 (03) 9549 7505
E-mail: sales@icom.net.au
URL: <http://www.icom.net.au>

Icom New Zealand

146A Harris Road, East Tamaki,
Auckland, New Zealand
Phone: +64 (09) 274 4062
Fax: +64 (09) 274 4708
E-mail: inquiries@icom.co.nz
URL: <http://www.icom.co.nz>

Icom (Europe) GmbH

Communication Equipment
Himmelgeister Str. 100,
D-40225 Düsseldorf, Germany
Phone: +49 (0211) 346047
Fax: +49 (0211) 333639
E-mail: info@icom-europe.com
URL: <http://www.icomeurope.com>

Icom Spain S.L.

Ctra. Rubi, No. 88 "Edificio Can Castanyer"
08190, Sant Cugat del Valles, Barcelona, Spain
Phone: +34 (93) 590 26 70
Fax: +34 (93) 589 04 46
E-mail: icom@icomspain.com
URL: <http://www.icomspain.com>

Icom (UK) Ltd.

Unit 9, Sea St., Herne Bay,
Kent, CT6 8LD, U.K.
Phone: +44 (01227) 741741
Fax: +44 (01227) 741742
E-mail: info@icomuk.co.uk
URL: <http://www.icomuk.co.uk>

Icom France S.a

Zac de la Plaine, 1,
Rue Brindejonc des Moulinais BP 5804,
31505 Toulouse Cedex, France
Phone: +33 (5) 61 36 03 03
Fax: +33 (5) 61 36 03 00
E-mail: icom@icom-france.com
URL: <http://www.icom-france.com>

Icom Polska

Sopot, 3 maja 54, Poland
Phone: +48 (58) 550 7135
Fax: +48 (58) 551 0484
E-mail: icompolska@icompolska.com.pl
URL: <http://www.icompolska.com.pl>

Asia Icom Inc.

6F No. 68, Sec. 1 Cheng-Teh Road,
Taipei, Taiwan, R.O.C.
Phone: +886 (02) 2559 1899
Fax: +886 (02) 2559 1874
E-mail: sales@asia-icom.com
URL: <http://www.asia-icom.com>

Beijing Icom Ltd.

10C07, Long Silver Mansion, No.88, Yong Ding
Road, Haidian District, Beijing, 100039, China
Phone: +86 (010) 5889 5391/5392/5393
Fax: +86 (010) 5889 5395
E-mail: bjicom@bjicom.com
URL: <http://www.bjicom.com>

Your local distributor/dealer:

Apex Radio Systems Ltd.
102 Tantobie Road
Denton Burn
Newcastle upon Tyne
NE15 7DU

Tel 0191 228 0466
Fax 0191 228 0467
Email info@apexradio.com

